

PROLINK®

Challenge The Limit

PRO600S INTERACTIVE UPS

ByPass Multiple Plug



Fax/Data Protection Sockets



- Lead Acid Maintenance Free Battery
- 100% Backup
- 100% Stabilized Output Power
- 2ms Typical Transfer Time
- Overload & Short Circuit Protection
- Power Factor of >70%
- 3:1 (Max) Crest Factor
- 12VDC DC Voltage for Battery
- 1 x 7AH Internal Battery

PRO600S INTERACTIVE UPS

Specifications

Ratings: 600VA

Input

Phase: Single+GND

Voltage Range: 160-275V

Frequency: 45-65Hz

Output

Voltage: 220VAC ($\pm 5\%$)

Waveform: PWM Simulated Sine Wave

Frequency: 50HZ $\pm 1\%$ or 60HZ $\pm 1\%$

Crest Factor: 3:1 (Max)

Transfer Time: 2ms typical

Surge

Energy Rating: 320 Joules Instantaneous Response

Test Standard: IEEE 587 Cat. A&B

Telephone Port: RJ11

Noise Filtering: EMI/RFI Full Time Suppression

Serial Port: RS232 with monitoring software

Battery

Recharge Time: 90% Capacity after 8 hours

Backup Time (minute): 15-40

Type: Lead-acid maintenance-free

General

Noise: <45dB

Temperature: 0°C -40°C

Humidity: 30%-90%

Net weigh: 7.5kgs

Shipping Weight: 8kgs

Dimension (cm): 37x14x23

Power Factor: >70%

**Specifications are subjected to change without prior notice*

Singapore

FIDA INTERNATIONAL (S) PTE LTD

Blk 105 Boon Keng Road #06-11/13

Kallang Basin Industrial Estate

Singapore 339776

Tel: (65) 6392 5567 Fax: (65) 6392 5455

Website: www.fida.com

Malaysia

FIDA SYSTEMS (M) SDN BHD

29 USJ 1/31

47600 Subang Jaya Selangor

Darul Ehsan Malaysia

Tel: (603) 8024 9151 Fax: (603) 8024 9161

Website: www.fida.com

<http://www.fida.com>

PROLINK is manufactured under the authority of **FIDA INTERNATIONAL (S) PTE LTD**



All brand or product names are trademark or registered trademarks of their respective owners
© Copyright 2004 PROLINK All Rights Reserved

Online Technical Support
support@fida.com

Free Lifetime Technical
Support Hotline

9am - 5.45pm (MON-FRI)

9am - 1pm (SAT)

Closed on Sundays & Public Holidays

Tel: (65) 6296 5455 (SINGAPORE)

(603) 8024 9151 (MALAYSIA)